

ABB 变频器 ACS800-01 (1.1~110kW) 适配的三相进线电抗器与三相输出电抗器

电源电压 V	电机功率 kW			ABB 变频器		三相进线电抗器				三相输出电抗器		结构号				
	正常	一般	重载	型号	额定电流 A	相电流 A	ABB 订货号	德云 订货号	结构号 A	ABB 订货号	德云 订货号					
3AC 380 400 415	1.5	1.5	1.1	ACS800-01-0003-3	5.1	8	ACS-CHK-B3	DY-SL03-102	1	15	NOCH0016-60 58983527	DY-SV03-01	1			
	2.2	2.2	1.5	ACS800-01-0004-3	6.5											
	3	3	2.2	ACS800-01-0005-3	8.5	8.5	10022673	DY-SL03-20	4							
	4	4	3	ACS800-01-0006-3	10.5	11.5	10022681	DY-SL03-21	5							
	5.5	5.5	4	ACS800-01-0009-3	13.9	16	10022690	DY-SL03-22	6							
	7.5	7.5	5.5	ACS800-01-0011-3	19	18.5	10015197	DY-SL03-23	6		28	NOCH0030-60 58983501		DY-SV03-02	3	
	11	11	7.5	ACS800-01-0016-3	25	27	10015201	DY-SL03-24	7							
	15	15	11	ACS800-01-0020-3	34	34	10015227	DY-SL03-25	6		65	NOCH0070-60 58983501		DY-SV03-03	8	
	22	18.5	15	ACS800-01-0025-3	44	42	10027233	DY-SL03-26	6							
	30	22	18.5	ACS800-01-0030-3	55	50	10015243	DY-SL03-27	7		105	NOCH0120-60 10030366		DY-SV03-04	10	
	37	30	22	ACS800-01-0040-3	72	68	10015251	DY-SL03-28	8							
	45	37	30	ACS800-01-0050-3	86	84	10027268	DY-SL03-29	9		225	NOCH0260-60 10030352		-B05	13	
	55	45	37	ACS800-01-0060-3	103	118	10064291	DY-SL03-30	1							
	75	55	45	ACS800-01-0070-3	141	160	10015286	DY-SL03-31	2		1	1				
	90	75	55	ACS800-01-0100-3	166											
110	90	75	ACS800-01-0120-3	202	200	10015294	DY-SL03-32	2								
3AC 380 400 415 440 460 480 500	2.2	2.2	1.5	ACS800-01-0004-3	4.9	8	ACS-CHK-B3	DY-SL03-102	1	15	NOCH0016-60 58983527	DY-SV03-01	1			
	3	3	2.2	ACS800-01-0005-3	6.2											
	4	4	3	ACS800-01-0006-3	8.1	8.5	10022673	DY-SL	5							
	5.5	5.5	4	ACS800-01-0009-3	10.5	11.5	10022681	DY-SL03-21	5							
	7.5	7.5	5.5	ACS800-01-0011-3	13.2	16	10022690	DY-SL03-22	6							
	11	11	7.5	ACS800-01-0016-3	19	18.5	10015197	DY-SL03-23	6		28	NOCH0030-60 58983501		DY-SV03-02	3	
	15	15	11	ACS800-01-0020-3	25	27	10015201	DY-SL03-24	7							
	18.5	18.5	15	ACS800-01-0025-3	34	34	10015227	DY-SL03-25	6		65	NOCH0070-60 58983501		DY-SV03-03	8	
	22	22	18.5	ACS800-01-0030-3	42	42	10027233	DY-SL03-26	6							
	30	30	22	ACS800-01-0040-3	48	50	10015243	DY-SL03-27	7		105	NOCH0120-60 10030366		DY-SV03-04	10	
	37	37	30	ACS800-01-0050-3	65	68	10015251	DY-SL03-28	8							
	45	45	37	ACS800-01-0060-3	79	84	10027268	DY-SL03-29	9		225	NOCH0260-60 10030352		DY-SV03-05	13	
	55	55	45	ACS800-01-0070-3	96	118	10064291	DY-SL03-30	1							
	75	75	55	ACS800-01-0100-3	124	160	10015286	DY-SL03-31	2		1	1				
	90	90	75	ACS800-01-0120-3	157											
110	1110	90	ACS800-01-0140-3	180	200	10015294	DY-SL03-32	2								

ABB 变频器 ACS800-04 (U4) (90~500kW) 适配的三相进线电抗器与三相输出电抗器

电源电压 V	电机功率 kW			ABB 变频器			三相进线电抗器				三相输出电抗器							
	正常	一般	重载	型号 ACS800-04	输入电流 A	输出电流 A	相电流 A	ABB 订货号	德云 订货号	结构	相电流 A	ABB 订货号	德云 订货号	结构号				
3AC 380~415	110	110	90	-0140-3	196	206	200	10015294	DY-SL03-32	12	225	NOCH0120-60 10030366	DY-SV03-05	13				
	132	132	110	-0170-3	237	248	240	10015308	DY-SL03-33	13	351	NOCH0400-60 10030340	DY-SV03-06	14				
	160	160	132	-0210-3	286	289	290	10015316	DY-SL03-34	13								
	200	200	160	-0260-3	438	445	540	10015341	DY-SL03-37	15	450	NOCH0260-60** 10030358	DY-SV03-07	14				
	250	250	200	-0320-3	501	521												
	315	315	250	-0400-3	581	602	710	10015324*	DY-SL03-351	15	702	NOCH0400-60** 10030340	DY-SV03-09	16				
	355	355	315	-0440-3	674	693												
	400	400	355	-0490-3	705	720												
3AC 380~500	132	132	110	-0170-5	191	196	200	10015294	DY-SL03-32	12	225	NOCH0120-60 10030366	DY-SV03-05	13				
	160	160	132	-0210-5	243	245	240	10015308	DY-SL03-33	13	351	NOCH0400-60 10030340	DY-SV03-06	14				
	200	200	160	-0260-5	291	289	290	10015316	DY-SL03-34	13								
	250	250	200	-0320-5	424	440	540	10015341	DY-SL03-37	15	450	NOCH0260-60** 10030358	DY-SV03-07	14				
	315	315	250	-0400-5	498	515												
	355	355	315	-0440-5	543	550	710	10015324*	DY-SL03-351	15	702	NOCH0400-60** 10030340	DY-SV03-09	16				
	400	400	355	-0490-5	590	602												
	450	450	400	-0550-5	669	684												
500	500	450	-0610-5	702	718													
3AC 525~690	132	110	90	-0140-7	126	134	132	10025923	DY-SL03-403	13	225	NOCH0120-60 10030366	DY-SV03-05	13				
	160	132	110	-0170-7	156	166	160	10015286	DY-SL03-31	12								
	160	160	132	-0210-7	158/191	166/203	200	10015294	DY-SL03-32	12								
	160/200	160/200	160	-0260-7	166/217	175/230	240	10015308	DY-SL03-33	13	450	NOCH0260-60** 10030358	DY-SV03-07	14				
	315	250	200	-0320-7	298	315	355	10015324	DY-SL03-35	14								
	355	315	250	-400-7	333	353	440	10015332	DY-SL03-36	14	710	10015324*	DY-SL03-351	15	702	NOCH0400-60** 10030340	DY-SV03-09	16
	400	355	315	-0440-7	377	396												
	450	400	355	-0490-7	423	445												
500	450	400	-0550-7	468	488													
560	500	450	-0610-7	533	560													

注: *两台进线电抗器接 Δ Y 两侧 **两台输出电抗器并联 ***三台输出电抗器并联